

# P1-BNCP/SMAP-141CJ-5

Cable Assembly, BNC Male to SMA Male, 141CJ Jacketed Conformable Coax, 5 inches

## **Product Features**

P1-BNCP/SMAP-141CJ-5 is a 50 Ohm RF cable that is part of P1dB's YouForm<sup>™</sup> conformable cable assembly series. It is a 5 inch SMA Male to BNC Plug Conformable cable assembly that utilizes 141CJ conformable coax with a diameter of 0.161 inches. The BNC cable assembly operates to 3 GHz with a max VSWR of 1.35:1.

YouForm<sup>™</sup> cables are conformable and jacketed conformable versions 085 and 141 semi-rigid coax cables and meet RG402 and RG405 dimensional and electrical specifications. YouForm<sup>™</sup> cable assemblies can operate up to 18 GHz, depending on the connector configuration. The advantage of YouForm<sup>™</sup> conformable cables over semi-rigid are their ability to be formed by hand multiple times, while semi-rigid cables can be formed only once with special bending tools.



## Electrical Specification: T Ambient = 25° C

| Parameter       | Frequency Range | Units | Min | Typical | Max | Notes |
|-----------------|-----------------|-------|-----|---------|-----|-------|
| Frequency Range |                 | GHz   | DC  |         | 3.0 |       |

### **Mechanical And Environmental Specifications:**

| Parameter       | Description           | Notes |  |
|-----------------|-----------------------|-------|--|
| Connector 1     | BNC Male              |       |  |
| Connector 2     | SMA Male              |       |  |
| Coax Cable      | Conformable, Jacketed |       |  |
| Cable Type      | 141CJ                 |       |  |
| Coax Diameter   | 0.161                 |       |  |
| Length          | 5.0                   |       |  |
| RoHS Compliance | HS Compliance Yes     |       |  |

#### **Product Notes**