

P1AT-SAMF-18G2W-6

RF Coaxial Attenuator, SMA Male to SMA Female, Bi-directional 50 Ohm, frequency to 18 GHz, 6 dB fixed, 2 Watt.

Product Features



Electrical Specification: $T_{\text{Ambient}} = 25^{\circ}\text{C}$

Parameter	Frequency Range	Units	Min	Typical	Max	Notes
Frequency Range		GHz	DC		18.0	

Mechanical And Environmental Specifications:

Parameter	Description	Notes
Connector 1	SMA Male	
Connector 2	SMA Female	
Length	0.86	
RoHS Compliance	Yes	

Product Notes