Cable Assembly, SMA Male to BNC Male, 085CC Conformable Coax, 18 inches

## **Product Features**

P1CA-SAMBNM-085CC-18 is a 50 Ohm RF Cable in P1dB's YouForm™ conformable cable assembly series. It is an 18 inch SMA Male to BNC Plug Conformable cable assembly that utilizes .085CC conformable coax with a diameter of 0.085 inches. The BNC cable assembly operates to 3 GHz with a max VSWR of 1.35:1.

YouForm<sup>TM</sup> cables are conformable and jacketed conformable versions 085 and 141 semi-rigid coax cables and meet RG402 and RG405 dimensional and electrical specifications. YouForm<sup>TM</sup> cable assemblies can operate up to 18 GHz, depending on the connector configuration. The advantage of YouForm<sup>TM</sup> conformable cables over semi-rigid are their ability to be formed by hand multiple times, while semi-rigid cables can be formed only once with special bending tools.



## **Electrical Specification: T**<sub>Ambient</sub> = 25° C

Parameter	Frequency Range	Units	Min	Typical	Max	Notes
Frequency Range		GHz	DC		3.0	

## **Mechanical And Environmental Specifications:**

Parameter	Description	Notes
Connector 1	SMA Male	
Connector 2	BNC Male	
Coax Cable	Conformable	
Cable Type	085CC	
Coax Diameter	0.09	
Length	18.0	
RoHS Compliance	Yes	

## **Product Notes**